

Project : F4WD  
Project Number : HI39700



P. O. Nr.

CDR  
Code

Seq.

Rev.

SBM Document Number : 001 . 39700 . 000XXX AK 004 - 00

SBM CDR Description : Equipment Index & Data Sheets

This document is part of VDB : VDB2

Supplier : KIDDE CHINA LIMITED

Address : 8F, Building A, New Bund  
World Trade Center No. 4,  
Lane 255 Dong Yu Road,  
Shanghai



Package Description : Gaseous Fire Fighting System Package

Vendor P. O. Reference :

Vendor Document Number : KD-1802-AK-004

Vendor Document Revision : 0

Document Title : Equipment Index & Data Sheets  
For Addressable Relay Output Device

Total Pages (incl. front page) : 2

Applicable Tag Number(s) :

Notes

---

---

---

# Addressable Relay Output Device



## FEATURES

- Full-Digital Communications
- Addressable Control Point
- Unpowered, SPDT Relay Contacts
- Control-by-Event And/or By Time Operation
- Status Indicator
- Unique Internal Supervision
- UL Listed
- FM Approved
- CSFM Approved

## DESCRIPTION

The SmartOne® Addressable Relay Output Device (AO) is an addressable output module for control of auxiliary equipment such as air handlers, door release and elevator recall.

The AO connects directly to a compatible control unit's signaling line circuit (SLC) and contains a SPDT relay to control auxiliary equipment. All of the electronics are contained in a small high-impact polymer case. This creates a small and durable device for installation.

## FIELD PROGRAMMING

The AO is field programmable with a unique four-digit address and a 40-character owner location message. The AO relay may be set or reset on command from the control unit.

In addition to combinational-logic programming that utilizes system inputs (i.e., events) to activate this device, the unit may be programmed for real-time clock operation. The real-time clock programming permits the AO to be activated and deactivated by the time of day, calendar date and day of the week.

## SUPERVISION

The AO is continuously monitored for:

- Internal power supply voltages
- Faulty entering of data into AO's memory
- Relay state equals command state

An internal set of relay contacts provides a feedback signal that confirms the activation of the addressable relay output. If the relay fails to operate at the appropriate time, the device transmits a trouble report for display by the control unit.

## STATUS LED

A status LED is mounted on the unit.



## SPECIFICATIONS

Input Voltage:

- 16.5 - 27.5 VDC

Standby Current:

- 400  $\mu$ A, Typical

Alarm Current:

- 400  $\mu$ A, Typical

Contact Ratings:

- Resistive Contact Rating:
  - 2 A @ 30 VDC
- Inductive Rating (Motor Control):
  - 1.0A @ 30 VDC, 0.6 PF.6A @ 120 VAC, 0.35 PF
- Pilot Duty
  - 0.6A @ 30 VDC, 0.35 PF

Operating Environment:

- -31°F - 151°F (-35°C - 66°C) at 0-95% RH

EMI Immunity:

- Meets UL 864

Dimensions:

- 2.3" x 1.8" x 0.8" nominal

Shipping Weight:

- 5.1 oz (145g)

LED Pulse Modes:

- Normal:
  - 9 second interval
- Trouble:
  - LED is off
- Alarm:
  - 2 second interval

Acceptable Wire Size:

- 14, 16, 18 AWG

Installation:

The AO can be mounted in a North American 1-1/2-in. (64 mm) deep 1-gang box, or standard 4-in. square box 1-1/2-in. (38 mm) deep with a cover.